

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}			0	-Fb ² /EJ	
	totali				2/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-2/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3 Fb^2/EJ$	$1/3 Xb/EJ$
CB b	$1-x/b$	$Fb-Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4 Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2 Fx$	$5/2 Fx$	1	$13/12 Fb^2/EJ$	$1/3 Xb/EJ$
DC b	1	$5/2 Fb-5/2 Fx$	$5/2 Fb-5/2 Fx$	1	0	0
DE b	$-1+x/b$	$-5/2 Fb+Fx$	$5/2 Fb-7/2 Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	0	0
ED b	x/b	$3/2 Fb+Fx$	$3/2 Fx+Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10 Fx+1/2 qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	$Fb-Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	$Fx-1/2 qx^2$	0	0	0	0
EB b	0	$-1/2 Fb+1/2 qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb^2/EJ	
	totali				$11/3 Fb^2/EJ$	$5/3 Xb/EJ$
	iperstatica $X=W_{cd}$				$-11/5 Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 7/4 x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (5/2 b - 7/4 b + 1/3 b) \cdot Fb \cdot 1/EJ = 13/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b + 1/3 b) \cdot Fb \cdot 1/EJ = 13/12 Fb^2/EJ$$



Schema di calcolo iperstatico




M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+Fx	5/2Fb-7/2Fx+Fx ² /b	1-2x/b+x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb+Fx	3/2Fx+Fx ² /b	x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				5/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{5}{4} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{5}{2} x - \frac{5}{4} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{5}{2} x - \frac{7}{4} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 7/4 b + 1/3 b) \cdot Fb \cdot 1/EJ = 13/12 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b + 1/3 b) \cdot Fb \cdot 1/EJ = 13/12 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+Fx	2Fx-Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+Fx	Fb-Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-Fx	1/2Fb+1/2Fx-Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-Fx	3/2Fx-Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				9/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-27/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - x^2/b^2) Fb 1/EJ dx = [1/2 x + 1/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+Fx	2Fx-Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+Fx	Fb-Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-Fx	1/2Fb+1/2Fx-Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-Fx	3/2Fx-Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - x^2/b^2) Fb 1/EJ dx = [1/2 x + 1/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + 1/2Fx$	$3/2Fx - 1/2Fx^2/b$	x^2/b^2	$7/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb + 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$7/12Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb - 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$7/12Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fb - 1/2Fx$	$3/2Fx - 1/2Fx^2/b$	x^2/b^2	$7/12Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	$Fx - 1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb + 1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$8/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica X=W _{cd}				$-8/5Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				2/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-2/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati

M_x flessione da iperstatica $X=1$



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$1/2Fx$	0	0	0	0
BA b	0	$-1/2Fb+1/2Fx$	0	0	0	0
BC b	$-x/b$	$1/2Fb-3/2Fx$	$-1/2Fx+3/2Fx^2/b$	x^2/b^2	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-3/2Fx$	$Fb-5/2Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb-3Fx$	$3Fb-3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-3Fb+3/2Fx$	$3Fb-9/2Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fb+3/2Fx$	$3/2Fx+3/2Fx^2/b$	x^2/b^2	$5/4Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	$-Fx$	0	0	0	0
GF b	0	$Fb-Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	Fb^2/EJ
	totali				$4Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-12/5Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (3/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+3/2Fx	3Fb-9/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb+3/2Fx	3/2Fx+3/2Fx ² /b	x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-6/5Fb	

Sviluppi di calcolo iperstatica

M_x , flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}				Fb ² /EJ	
	totali				8/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-8/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$





Schema di calcolo iperstatico




M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫xM _x M ₀ /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				2/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-2/5Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fx-Fx	2Fx-Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+Fx	Fb-Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-Fx+1/2qx ²	Fb-3/2Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2qx ²	3/2Fx-1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				19/24Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-19/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [3/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$



⊕ F_b

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$



Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$1/2Fx$	0	0	0	0
BA b	0	$-1/2Fb+1/2Fx$	0	0	0	0
BC b	$-x/b$	$1/2Fb-3/2Fx$	$-1/2Fx+3/2Fx^2/b$	x^2/b^2	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-3/2Fx$	$Fb-5/2Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb+3/2Fx$	$5/2Fb-4Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$Fb+3/2Fx$	$Fb+3/2Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	$-Fb+Fx$	0	0	0	0
GA 2b	0	$2Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	$-3Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$7/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-21/10Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fb+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-9/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-5/4Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$




\oplus F_b



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-1/2Fx-1/2qx ²	0	0	0	0
BA b	0	Fb-3/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				5/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/2Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx-1/2qx ²	0	0	0	0
BA b	0	Fb-3/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	3/2Fb ² /EJ	Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	7/6Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} - L_{BE}$				Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-23/10Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF $\sqrt{5}b$	0	4 $\sqrt{5}$ Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				11/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-11/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x^2/b^2	$1/2 Fb^2/EJ$	$1/3 Xb/EJ$
CB b	$1-x/b$	Fb	Fb-Fx	$1-2x/b+x^2/b^2$	$1/2 Fb^2/EJ$	$1/3 Xb/EJ$
CD b	-1	-Fx	Fx	1	$1/2 Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2 Fb^2/EJ$	$1/3 Xb/EJ$
DE b	$-1+x/b$	-Fb	Fb-Fx	$1-2x/b+x^2/b^2$	$1/2 Fb^2/EJ$	$1/3 Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$1/2 Fx + 1/2 qx^2$	0	0	0	0
GF b	0	$-Fb + 3/2 Fx - 1/2 qx^2$	0	0	0	0
GA 2b	0	$2Fb - 1/2 qx^2$	0	0	0	0
AG 2b	0	$-2Fx + 1/2 qx^2$	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$5/2 Fb^2/EJ$	$5/3 Xb/EJ$
	iperstatica $X=W_{cd}$				$-3/2 Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	1/2Fb ² /EJ	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	1/2Fx+1/2qx ²	0	0	0	0
GF b	0	-Fb+3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + 1/3 x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + 1/3 x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/2 x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 \cdot Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 \cdot Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	13/12Fb ² /EJ	1/3Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+Fx	5/2Fb-7/2Fx+Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	3/2Fb+Fx	3/2Fx+Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}			0	Fb ² /EJ	
	totali				11/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-11/5Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + x^2/b^2) Fb 1/EJ dx = [5/2 x - 7/4 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 7/4 b + 1/3 b) Fb 1/EJ = 13/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b + x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/3 b) Fb 1/EJ = 13/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+Fx	5/2Fb-7/2Fx+Fx ² /b	1-2x/b+x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb+Fx	3/2Fx+Fx ² /b	x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				5/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + x^2/b^2) Fb 1/EJ dx = [5/2 x - 7/4 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 7/4 b + 1/3 b) Fb 1/EJ = 13/12 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (3/2 x/b + x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/3 b) Fb 1/EJ = 13/12 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fb+3/2Fx	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} L_{BE}$				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-21/10Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



\oplus F_b



Schema di calcolo iperstatico




(+) M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M ₀ /EJdx
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	0	0
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-9/10Fb	

Sviluppi di calcolo iperstatica

(+) M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/lb	-Fx	Fx ² /lb	x ² /lb ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/lb	Fb-Fx	Fb-2Fx+Fx ² /lb	1-2x/lb+x ² /lb ²	11/12Fb ² /EJ	Xb/EJ
CD b	-1	-3/2Fx-1/2qx ²	3/2Fx+1/2Fx ² /lb	1		
DC b	1	2Fb-5/2Fx+1/2qx ²	2Fb-5/2Fx+1/2Fx ² /lb	1		
DE b	-1+x/lb	-2Fb+Fx	2Fb-3Fx+Fx ² /lb	1-2x/lb+x ² /lb ²	5/6Fb ² /EJ	1/3Xb/EJ
ED b	x/lb	Fb+Fx	Fx+Fx ² /lb	x ² /lb ²		
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} = L_{BE}$				Fb ² /EJ	
	totali				37/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}					-37/20Fb

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b + \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b + 1/6 b) \cdot Fb \cdot 1/EJ = 11/12 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[2x - \frac{5}{4} x^2/b + \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (2b - 5/4 b + 1/6 b) \cdot Fb \cdot 1/EJ = 11/12 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (2 - 3x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[2x - \frac{3}{2} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (2b - 3/2 b + 1/3 b) \cdot Fb \cdot 1/EJ = 5/6 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/3 b) \cdot Fb \cdot 1/EJ = 5/6 \cdot Fb^2/EJ$$





Schema di calcolo iperstatico




Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/lb	-Fx	Fx^2/lb	x^2/lb^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/lb	Fb-Fx	$Fb-2Fx+Fx^2/lb$	$1-2x/lb+x^2/lb^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-3/2Fx-1/2qx^2$	$3/2Fx+1/2Fx^2/lb$	1	$11/12Fb^2/EJ$	Xb/EJ
DC b	1	$2Fb-5/2Fx+1/2qx^2$	$2Fb-5/2Fx+1/2Fx^2/lb$	1	$11/12Fb^2/EJ$	Xb/EJ
DE b	-1+x/lb	-2Fb+Fx	$2Fb-3Fx+Fx^2/lb$	$1-2x/lb+x^2/lb^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/lb	Fb+Fx	$Fx+Fx^2/lb$	x^2/lb^2	$5/6Fb^2/EJ$	$1/3Xb/EJ$
EF √5b	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$13/12Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/20Fb$	

Sviluppi di calcolo iperstatica

(+) M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= [3/4 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (3/4 b + 1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$


$$= (2b - 5/4 b + 1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/12 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (2 - 3x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [2x - 3/2 x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (2b - 3/2 b + 1/3 b) \cdot Fb \cdot 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/3 b) \cdot Fb \cdot 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico




M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	Fx-1/2qx ²	0	0	0	0
BA b	0	-1/2Fb+1/2qx ²	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1		
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²		
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-21/10Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-5/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [-5/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-5/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 9/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [x - 9/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 9/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx = [9/4 x^2/b]_0^b Fb 1/EJ$$

$$= (9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ$$



$$= (9/2 b - 9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (9/2 - 8x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 4x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 4b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$5/2Fx$	0	0	0	0
BA b	0	$-5/2Fb+5/2Fx$	0	0	0	0
BC b	$-x/b$	$5/2Fb-7/2Fx$	$-5/2Fx+7/2Fx^2/b$	x^2/b^2	$-1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-7/2Fx$	$Fb-9/2Fx+7/2Fx^2/b$	$1-2x/b+x^2/b^2$	$-1/12Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-9/2Fx$	$9/2Fx$	1	$9/4Fb^2/EJ$	Xb/EJ
DC b	1	$9/2Fb-9/2Fx$	$9/2Fb-9/2Fx$	1	$9/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-9/2Fb+7/2Fx$	$9/2Fb-8Fx+7/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+7/2Fx$	$Fx+7/2Fx^2/b$	x^2/b^2	$5/3Fb^2/EJ$	$1/3Xb/EJ$
EF √5b	0	$11\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	$Fb-Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$8Fb-3Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-5Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$17/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-17/10Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-5/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [-5/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-5/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 9/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [x - 9/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 9/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/2 b - 9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (9/2 - 8x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 4x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 4b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-9/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M₁ flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0		
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	5/2Fx	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	$-5/2Fb+Fx+1/2qx^2$	$5/2Fb-7/2Fx+1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$25/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+2Fx-1/2qx^2$	$Fx+2Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$29/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-87/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + 1/2 x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx$$

$$= [5/2 x - 7/4 x^2/b + 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 7/4 b + 1/6 b + 1/8 b) \cdot Fb \cdot 1/EJ = 25/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 2/3 b - 1/8 b) \cdot Fb \cdot 1/EJ = 25/24 Fb^2/EJ$$



Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0		
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	5/2Fx	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	$-5/2Fb+Fx+1/2qx^2$	$5/2Fb-7/2Fx+1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$25/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+2Fx-1/2qx^2$	$Fx+2Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$13/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-39/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + 1/2 x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx$$

$$= [5/2 x - 7/4 x^2/b + 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 7/4 b + 1/6 b + 1/8 b) \cdot Fb \cdot 1/EJ = 25/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 2/3 b - 1/8 b) \cdot Fb \cdot 1/EJ = 25/24 Fb^2/EJ$$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - x^2/b^2) Fb 1/EJ dx = [1/2 x + 1/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$





Schema di calcolo iperstatico




M₀ flessione da carichi assegnati

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+Fx	2Fx-Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+Fx	Fb-Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-Fx	1/2Fb+1/2Fx-Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-Fx	3/2Fx-Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/20Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - x^2/b^2) Fb 1/EJ dx = [1/2 x + 1/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-5/4Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/lb	-Fx	Fx^2/lb	x^2/lb^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/lb	Fb-Fx	$Fb-2Fx+Fx^2/lb$	$1-2x/lb+x^2/lb^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-3/2Fx-1/2qx^2$	$3/2Fx+1/2Fx^2/lb$	1	$11/12Fb^2/EJ$	Xb/EJ
DC b	1	$2Fb-5/2Fx+1/2qx^2$	$2Fb-5/2Fx+1/2Fx^2/lb$	1	$11/12Fb^2/EJ$	Xb/EJ
DE b	-1+x/lb	-2Fb+Fx	$2Fb-3Fx+Fx^2/lb$	$1-2x/lb+x^2/lb^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/lb	Fb+Fx	$Fx+Fx^2/lb$	x^2/lb^2	$5/6Fb^2/EJ$	$1/3Xb/EJ$
EF √5b	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} L_{BE}$				Fb^2/EJ	
	totali				$37/12Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-37/20Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 \, b) \cdot Fb \cdot 1/EJ = 1/3 \, Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot Fb \cdot 1/EJ = 1/3 \, Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b + \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 \, b + 1/6 \, b) \cdot Fb \cdot 1/EJ = 11/12 \, Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[2x - \frac{5}{4} x^2/b + \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (2b - 5/4 \, b + 1/6 \, b) \cdot Fb \cdot 1/EJ = 11/12 \, Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (2 - 3x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[2x - \frac{3}{2} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (2b - 3/2 \, b + 1/3 \, b) \cdot Fb \cdot 1/EJ = 5/6 \, Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b + 1/3 \, b) \cdot Fb \cdot 1/EJ = 5/6 \, Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/4 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (2b - 5/4 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/12 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (2 - 3x/b + x^2/b^2) Fb 1/EJ dx = [2x - 3/2 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2b - 3/2 b + 1/3 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/3 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-5/4Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ^ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



$M_0(x)$ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-2Fx-1/2qx ²	2Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-3Fx+1/2qx ²	5/2Fb-3Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				41/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-41/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-2Fx-1/2qx ²	2Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-3Fx+1/2qx ²	5/2Fb-3Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				17/12Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-17/20Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico



M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-5/4Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -5/6 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= \left[\frac{1}{2} x - \frac{1}{2} x^2/b + \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -5/6 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0		
BC b	-x/b	-2Fb+Fx	$2Fx-Fx^2/b$	x^2/b^2	$2/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb+Fx	$Fb-Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb-Fx+1/2qx^2$	$1/2Fb+1/2Fx-3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb-1/2qx^2$	$Fx-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$53/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-53/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x^2/b - 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx$$


$$= [1/2 x + 1/4 x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/4 b - 1/2 b + 1/8 b) \cdot Fb \cdot 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/8 b) \cdot Fb \cdot 1/EJ = 3/8 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0		
BC b	-x/b	-2Fb+Fx	$2Fx-Fx^2/b$	x^2/b^2	$2/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb+Fx	$Fb-Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb-Fx+1/2qx^2$	$1/2Fb+1/2Fx-3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb-1/2qx^2$	$Fx-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$5/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-1/8Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$


$$= [1/2 x + 1/4 x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/2 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + 1/2Fx$	$3/2Fx - 1/2Fx^2/b$	x^2/b^2	$7/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb + 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$7/12Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb - 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$7/12Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fb - 1/2Fx$	$3/2Fx - 1/2Fx^2/b$	x^2/b^2	$7/12Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	$Fx - 1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb + 1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} = \epsilon_{BE} = L_{BE}$				Fb^2/EJ	
	totali				$8/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-8/5Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				2/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-2/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[x - 1/2 x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{CD}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$-1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$Fb - 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fb$	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	Fb	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb$	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	$-Fb+Fx$	0	0	0	0
GA 2b	0	$2Fb - 1/2qx^2$	0	0	0	0
AG 2b	0	$-2Fx + 1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$5/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-3/2Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx-1/2qx ²	0	0	0	0
BA b	0	Fb-3/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$


$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	Fx-1/2qx ²	0	0	0	0
BA b	0	-1/2Fb+1/2qx ²	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1		
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²		
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-21/10Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fb + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$1/2Fb - 3/2Fx$	$-1/2Fx + 3/2Fx^2/b$	x^2/b^2	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 3/2Fx$	$Fb - 5/2Fx + 3/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb + 3/2Fx$	$5/2Fb - 4Fx + 3/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$Fb + 3/2Fx$	$Fx + 3/2Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	$Fb - Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$3/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-9/10Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE-E} L _{BE-E}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-5/4Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫xM _x M _x /EJdx
AB b	0	3/2Fx-1/2qx ²	0	0	0	0
BA b	0	-Fb+1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-23/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$3/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-Fb + 1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$Fb - 2Fx$	$-Fx + 2Fx^2/b$	x^2/b^2	$1/6Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 2Fx$	$Fb - 3Fx + 2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$1/6Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb - 3Fx$	$3Fb - 3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1 + x/b$	$-3Fb + 2Fx$	$3Fb - 5Fx + 2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$7/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb + 2Fx$	$Fx + 2Fx^2/b$	x^2/b^2	$7/6Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$4\sqrt{5}/5Fx$	0	0	0	0
FG b	0	$-Fx$	0	0	0	0
GF b	0	$Fb - Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$4Fb - Fx - 1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx + 1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$11/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-11/10Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{CD}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$-1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$Fb - 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fb$	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	Fb	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb$	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-3/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$Fb - 1/2Fx - 1/2qx^2$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$5/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-3/2Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 \, b) \cdot 1/EJ = 1/3 \, b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 \, b) \cdot Fb \cdot 1/EJ = 1/2 \, Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$-1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$Fb - 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fb$	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	Fb	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb$	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-3/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$Fb - 1/2Fx - 1/2qx^2$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$1/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-3/10Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$





Schema di calcolo iperstatico




(+) M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + 1/2Fx$	$3/2Fx - 1/2Fx^2 / b$	x^2 / b^2	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CB b	$1-x/b$	$Fb + 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2 / b$	$1 - 2x/b + x^2 / b^2$	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DC b	1	Fb - Fx	Fb - Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DE b	$-1 + x/b$	$-Fb - 1/2Fx + 1/2qx^2$	$Fb - 1/2Fx - Fx^2 / b + 1/2qx^3 / b$	$1 - 2x/b + x^2 / b^2$	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
ED b	x/b	$Fb + 1/2Fx - 1/2qx^2$	$Fx + 1/2Fx^2 / b - 1/2qx^3 / b$	x^2 / b^2	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb - Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb^2 / EJ	Fb^2 / EJ
	totali				$21/8Fb^2 / EJ$	$5/3Xb / EJ$
	iperstatica $X=W_{cd}$				$-63/40Fb$	

Sviluppi di calcolo iperstatica



(+) M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx-1/2qx ²	0	0	0	0
BA b	0	3/2Fb-2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ² /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ² /b	x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}			0	-Fb ² /EJ	0
	totali				5/8Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-3/8Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+3/2Fx	3Fb-9/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb+3/2Fx	3/2Fx+3/2Fx ² /b	x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-12/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+3/2Fx	3Fb-9/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb+3/2Fx	3/2Fx+3/2Fx ² /b	x ² /b ²	5/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-6/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/2 b) Fb 1/EJ = 5/4 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	7/6Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-23/10Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-5/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [-5/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-5/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 9/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [x - 9/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 9/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx = [9/4 x^2/b]_0^b Fb 1/EJ$$

$$= (9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ$$

$$= (9/2 b - 9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (9/2 - 8x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 4x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 4b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-5/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [-5/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-5/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 9/2 x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [x - 9/4 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 9/4 b + 7/6 b) Fb 1/EJ = -1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (9/2 b - 9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (9/2 - 8x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 4x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (9/2 b - 4b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 7/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 7/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 7/6 b) Fb 1/EJ = 5/3 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0	0	0
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CD b	-1	-2Fx-1/2qx ²	2Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-3Fx+1/2qx ²	5/2Fb-3Fx+1/2Fx ² /b	1	7/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE- BE}}$				Fb ² /EJ	
	totali				41/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-41/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[-1/4 x^2/b + 1/2 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-1/4 b + 1/2 b) \cdot Fb \cdot 1/EJ = 1/4 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 5/4 x^2/b + 1/2 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 5/4 b + 1/2 b) \cdot Fb \cdot 1/EJ = 1/4 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x^2/b + 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b + 1/6 b) \cdot Fb \cdot 1/EJ = 7/6 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[5/2 x - 3/2 x^2/b + 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 7/6 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[5/2 x - 2x^2/b + 1/2 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) \cdot Fb \cdot 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[1/2 x^2/b + 1/2 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/2 b) \cdot Fb \cdot 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{CD}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$1/2Fx$	0	0	0	0
BA b	0	$-1/2Fb+1/2Fx$	0	0	0	0
BC b	$-x/b$	$1/2Fb-3/2Fx$	$-1/2Fx+3/2Fx^2/b$	x^2/b^2	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-3/2Fx$	$Fb-5/2Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-2Fx-1/2qx^2$	$2Fx+1/2Fx^2/b$	1	$7/6Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-3Fx+1/2qx^2$	$5/2Fb-3Fx+1/2Fx^2/b$	1	$7/6Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb+3/2Fx$	$5/2Fb-4Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$Fb+3/2Fx$	$Fx+3/2Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$4\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	$Fb-Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$17/12Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-17/20Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫xM _x M _x /EJdx
AB b	0	3/2Fx-1/2qx ²	0	0	0	0
BA b	0	-Fb+1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}			0	Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-23/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫xM _x M _x /EJdx
AB b	0	3/2Fx-1/2qx ²	0	0	0	0
BA b	0	-Fb+1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}			0	-Fb ² /EJ	5/3Xb/EJ
	totali				11/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-11/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-23/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$





$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	3/2Fb ² /EJ	Xb/EJ
CD b	-1	-3Fx	3Fx	1	7/6Fb ² /EJ	1/3Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$			0	-Fb ² /EJ	
	totali				11/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-11/10Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0		
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²		
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1		
DE b	-1+x/b	-3Fb+3/2Fx+1/2qx ²	3Fb-9/2Fx+Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	29/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+5/2Fx-1/2qx ²	Fb+5/2Fx ² /b-1/2qx ³ /b	x ² /b ²		
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				95/24Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-19/8Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0		
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²		
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1		
DE b	-1+x/b	-3Fb+3/2Fx+1/2qx ²	3Fb-9/2Fx+Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	29/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+5/2Fx-1/2qx ²	Fx+5/2Fx ² /b-1/2qx ³ /b	x ² /b ²		
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{iCD} \epsilon_{CD} L_{CD}$				-Fb ² /EJ	
	totali				47/24Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-47/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}				Fb ² /EJ	
	totali				8/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-8/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫xM _x M ₀ /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				2/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-2/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[x - 1/2 x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flexione da carichi assegnati



M_x flexione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	1/2Fb ² /EJ	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	1/2Fx+1/2qx ²	0	0	0	0
GF b	0	-Fb+3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				5/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/2Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	1/2Fx+1/2qx ²	0	0	0	0
GF b	0	-Fb+3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-3/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$1/2Fx$	0	0	0	0
BA b	0	$-1/2Fb+1/2Fx$	0	0	0	0
BC b	$-x/b$	$1/2Fb-3/2Fx$	$-1/2Fx+3/2Fx^2/b$	x^2/b^2	$1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-3/2Fx$	$Fb-5/2Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb+3/2Fx$	$5/2Fb-4Fx+3/2Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$Fb+3/2Fx$	$Fx+3/2Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-3/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$Fb-1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	$-3Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$3/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-9/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} -L _{BE}				Fb ² /EJ	
	totali				25/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-5/4Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/6 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$-1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$Fb - 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fb$	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	Fb	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb$	$Fb-Fx$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-3/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$Fb - 1/2Fx - 1/2qx^2$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$5/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-3/2Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$



Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx-1/2qx ²	0	0	0	0
BA b	0	Fb-3/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-3/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	7/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb ² /EJ	
	totali				23/6Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-23/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	3/2Fb ² /EJ	Xb/EJ
CD b	-1	-3Fx	3Fx	1	0	0
DC b	1	3Fb-3Fx	3Fb-3Fx	1	7/6Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-3Fb+2Fx	3Fb-5Fx+2Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	Fb+2Fx	Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$			0	-Fb ² /EJ	
	totali				11/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-11/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				21/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-63/40Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$



Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				5/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-3/8Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{3}{4} x^2/b - \frac{1}{6} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/6 x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = \left[x - 1/2 x^2/b \right]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 \cdot Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = \left[x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 \cdot Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 \cdot Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fx-Fx	2Fx-Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+Fx	Fb-Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-Fx+1/2qx ²	Fb-3/2Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2qx ²	3/2Fx-1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				19/24Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-19/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [3/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} l_{cd}$				-Fb ² /EJ	
	totali				5/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-3/8Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$


$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$



Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M₁ flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0		
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	5/2Fx	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	$-5/2Fb+Fx+1/2qx^2$	$5/2Fb-7/2Fx+1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$25/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+2Fx-1/2qx^2$	$Fx+2Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$29/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-87/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$

$$= [5/2 x - 7/4 x^2/b + 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (5/2 b - 7/4 b + 1/6 b + 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (1/2 b + 2/3 b - 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0		
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	5/2Fx	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	$-5/2Fb+Fx+1/2qx^2$	$5/2Fb-7/2Fx+1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$25/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+2Fx-1/2qx^2$	$Fx+2Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$13/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-39/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 7/2 x/b + 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$

$$= [5/2 x - 7/4 x^2/b + 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (5/2 b - 7/4 b + 1/6 b + 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (1/2 b + 2/3 b - 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0		
BC b	-x/b	-2Fb+Fx	$2Fx-Fx^2/b$	x^2/b^2	$2/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb+Fx	$Fb-Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb-Fx+1/2qx^2$	$1/2Fb+1/2Fx-3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb-1/2qx^2$	$Fx-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$53/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-53/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x^2/b - 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx$$


$$= [1/2 x + 1/4 x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/4 b - 1/2 b + 1/8 b) \cdot Fb \cdot 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/8 b) \cdot Fb \cdot 1/EJ = 3/8 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0		
BC b	-x/b	-2Fb+Fx	$2Fx-Fx^2/b$	x^2/b^2	$2/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb+Fx	$Fb-Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb-Fx+1/2qx^2$	$1/2Fb+1/2Fx-3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb-1/2qx^2$	$Fx-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$5/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-1/8Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - x^2/b^2) Fb 1/EJ dx = [x^2/b - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x^2/b^2) Fb 1/EJ dx = [x - 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 + 1/2 x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$


$$= [1/2 x + 1/4 x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/4 b - 1/2 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + 1/2Fx$	$3/2Fx - 1/2Fx^2 / b$	x^2 / b^2	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CB b	$1-x/b$	$Fb + 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2 / b$	$1 - 2x/b + x^2 / b^2$	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DE b	$-1+x/b$	$-Fb - 1/2Fx + 1/2qx^2$	$Fb - 1/2Fx - Fx^2 / b + 1/2qx^2 / b$	$1 - 2x/b + x^2 / b^2$	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
ED b	x/b	$Fb + 1/2Fx - 1/2qx^2$	$Fx + 1/2Fx^2 / b - 1/2qx^3 / b$	x^2 / b^2	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb^2 / EJ	Fb^2 / EJ
	totali				$21/8Fb^2 / EJ$	$5/3Xb / EJ$
	iperstatica $X=W_{cd}$				$-63/40Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + 1/2Fx$	$3/2Fx - 1/2Fx^2 / b$	x^2 / b^2	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CB b	$1-x/b$	$Fb + 1/2Fx$	$Fb - 1/2Fx - 1/2Fx^2 / b$	$1 - 2x/b + x^2 / b^2$	$7/12Fb^2 / EJ$	$1/3Xb / EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DC b	1	Fb - Fx	Fb - Fx	1	$1/2Fb^2 / EJ$	Xb / EJ
DE b	$-1 + x/b$	$-Fb - 1/2Fx + 1/2qx^2$	$Fb - 1/2Fx - Fx^2 / b + 1/2qx^2 / b$	$1 - 2x/b + x^2 / b^2$	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
ED b	x/b	$Fb + 1/2Fx - 1/2qx^2$	$Fx + 1/2Fx^2 / b - 1/2qx^3 / b$	x^2 / b^2	$13/24Fb^2 / EJ$	$1/3Xb / EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb - Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \cdot \epsilon_{cd} \cdot L_{cd}$			0	$-Fb^2 / EJ$	0
	totali				$5/8Fb^2 / EJ$	$5/3Xb / EJ$
	iperstatica $X=W_{cd}$				$-3/8Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0		
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²		
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1		
DE b	-1+x/b	-3Fb+3/2Fx+1/2qx ²	3Fb-9/2Fx+Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	29/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+5/2Fx-1/2qx ²	Fx+5/2Fx ² /b-1/2qx ³ /b	x ² /b ²		
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				95/24Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-19/8Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$



Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	1/2Fx	0	0	0	0
BA b	0	-1/2Fb+1/2Fx	0	0		
BC b	-x/b	1/2Fb-3/2Fx	-1/2Fx+3/2Fx ² /b	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx	Fb-5/2Fx+3/2Fx ² /b	1-2x/b+x ² /b ²		
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1		
DE b	-1+x/b	-3Fb+3/2Fx+1/2qx ²	3Fb-9/2Fx+Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	29/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+5/2Fx-1/2qx ²	Fx+5/2Fx ² /b-1/2qx ³ /b	x ² /b ²		
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0		
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0		
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \varepsilon_{CD} L_{CD}$				-Fb ² /EJ	
	totali				47/24Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-47/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [-1/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [x - 5/4 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 1/2 b) Fb 1/EJ = 1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 9/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3x - 9/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3b - 9/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 29/24 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				21/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-63/40Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/6 b) \cdot Fb \cdot 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx	Fb-1/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-3/2Fx+1/2qx ²	0	0	0	0
GF b	0	Fb-1/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				5/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-3/8Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+3/2Fx-1/2qx ²	2Fx-3/2Fx ² /b+1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx+1/2qx ²	Fb-1/2Fx-1/2qx ³ /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				66/24Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-13/8Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+3/2Fx-1/2qx ²	2Fx-3/2Fx ² /b+1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx+1/2qx ²	Fb-1/2Fx-1/2qx ³ /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx	Fb-1/2Fx-1/2Fx ² /b	1-2x/b+x ² /b ²	7/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3/2Fb-1/2Fx	3/2Fx-1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				17/24Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-17/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/6 b) Fb 1/EJ = 7/12 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-3/2Fx	0	0	0	0
BA b	0	3/2Fb-3/2Fx	0	0	0	0
BC b	-x/b	-3/2Fb+Fx-1/2qx ²	3/2Fx-Fx ² /b+1/2qx ³ /b	x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2qx ²	Fb-Fx+1/2Fx ² /b-1/2qx ³ /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb	Fb-Fx	1-2x/b+x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb	Fx	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	Fx	0	0	0	0
GF b	0	-Fb+Fx	0	0	0	0
GA 2b	0	2Fb-1/2qx ²	0	0	0	0
AG 2b	0	-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				13/24Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-13/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	$-1/2Fx - 1/2qx^2$	$1/2Fx^2/b + 1/2qx^3/b$	x^2/b^2	$7/24Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 3/2Fx + 1/2qx^2$	$Fb - 5/2Fx + 2Fx^2/b - 1/2qx^3/b$	$1 - 2x/b + x^2/b^2$	$7/24Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb + 3/2Fx$	$5/2Fb - 4Fx + 3/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$Fb + 3/2Fx$	$Fx + 3/2Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	$Fb - Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$85/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-17/8Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/6 b + 1/8 b) Fb 1/EJ = 7/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 5/4 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 2/3 b - 1/8 b) Fb 1/EJ = 7/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico




M₀ flessione da carichi assegnati

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-1/2Fx-1/2qx ²	1/2Fx ² /b+1/2qx ³ /b	x ² /b ²	7/24Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-3/2Fx+1/2qx ²	Fb-5/2Fx+2Fx ² /b-1/2qx ³ /b	1-2x/b+x ² /b ²	7/24Fb ² /EJ	1/3Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+3/2Fx	5/2Fb-4Fx+3/2Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+3/2Fx	Fx+3/2Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				37/24Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-37/40Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/6 b + 1/8 b) Fb 1/EJ = 7/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 5/2 x/b + 2x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 5/4 x^2/b + 2/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 5/4 b + 2/3 b - 1/8 b) Fb 1/EJ = 7/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 4x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 2x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 2b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 3/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 1/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/2 b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+3/2Fx-1/2qx ²	2Fx-3/2Fx ² /b+1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx+1/2qx ²	Fb-1/2Fx-1/2qx ³ /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb-1/2Fx	1/2Fb-1/2Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb-1/2Fx	Fx-1/2Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF $\sqrt{5}b$	0	2\sqrt{5}5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				1/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-3/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b - 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b - 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/6 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	$-Fx - 1/2qx^2$	0	0	0	0
BA b	0	$3/2Fb - 2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-3/2Fb + Fx - 1/2qx^2$	$3/2Fx - Fx^2/b + 1/2qx^3/b$	x^2/b^2	$13/24Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb + 1/2qx^2$	$Fb - Fx + 1/2Fx^2/b - 1/2qx^3/b$	$1 - 2x/b + x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb - Fx	Fb - Fx	1	$1/2Fb^2/EJ$	$1/3Xb/EJ$
DE b	$-1 + x/b$	-Fb	Fb - Fx	$1 - 2x/b + x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb - Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb - Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$13/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/40Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [-1/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$1/2Fx$	0	0	0	0
BA b	0	$-1/2Fb+1/2Fx$	0	0	0	0
BC b	$-x/b$	$1/2Fb-Fx-1/2qx^2$	$-1/2Fx+Fx^2/b+1/2qx^3/b$	x^2/b^2	$5/24Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-2Fx+1/2qx^2$	$Fb-3Fx+5/2Fx^2/b-1/2qx^3/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb-3Fx$	$3Fb-3Fx$	1		
DE b	$-1+x/b$	$-3Fb+2Fx$	$3Fb-5Fx+2Fx^2/b$	$1-2x/b+x^2/b^2$	$7/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+2Fx$	$Fx+2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$4\sqrt{5}/5Fx$	0	0	0	0
FG b	0	$-Fx$	0	0	0	0
GF b	0	$Fb-Fx$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$15/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-9/8Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-1/2 x/b + x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [-1/4 x^2/b + 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (-1/4 b + 1/3 b + 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 5/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/2 x^2/b + 5/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 5/6 b - 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 5x/b + 2x^2/b^2) Fb 1/EJ dx = [3x - 5/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 5/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 2x^2/b^2) Fb 1/EJ dx = [1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b + 2/3 b) Fb 1/EJ = 7/6 Fb^2/EJ$$



Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$-3/2Fx$	0	0	0	0
BA b	0	$3/2Fb-3/2Fx$	0	0	0	0
BC b	$-x/b$	$-3/2Fb+Fx-1/2qx^2$	$3/2Fx-Fx^2/b+1/2qx^3/b$	x^2/b^2	$13/24Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb+1/2qx^2$	$Fb-Fx+1/2Fx^2/b-1/2qx^3/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1		
DE b	$-1+x/b$	-Fb	Fb-Fx	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fb	Fx	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-3/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$Fb-1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$13/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/40Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (3/2 x/b - x^2/b^2 + 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [3/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/4 b - 1/3 b + 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b + 1/6 b - 1/8 b) \cdot Fb \cdot 1/EJ = 13/24 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	-2Fb+3/2Fx-1/2qx ²	2Fx-3/2Fx ² /b+1/2qx ³ /b	x ² /b ²	5/8Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb+1/2Fx+1/2qx ²	Fb-1/2Fx-1/2qx ³ /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb-1/2Fx+1/2qx ²	Fb-1/2Fx-Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	13/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fb+1/2Fx-1/2qx ²	Fx+1/2Fx ² /b-1/2qx ³ /b	x ² /b ²	0	0
EF 1/5b	0	2\sqrt{5}5Fx	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				8/3Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-8/5Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$


$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$



Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-2Fx	0	0	0	0
BA b	0	2Fb-2Fx	0	0	0	0
BC b	-x/b	$-2Fb+3/2Fx-1/2qx^2$	$2Fx-3/2Fx^2/b+1/2qx^3/b$	x^2/b^2	$5/8Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	$Fb+1/2Fx+1/2qx^2$	$Fb-1/2Fx-1/2qx^3/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1		
DE b	-1+x/b	$-Fb-1/2Fx+1/2qx^2$	$Fb-1/2Fx-Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$13/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fb+1/2Fx-1/2qx^2$	$Fx+1/2Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF 1/5b	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-Fx	0	0	0	0
GF b	0	Fb-Fx	0	0	0	0
GA 2b	0	0	0	0	0	0
AG 2b	0	0	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \cdot \epsilon_{cd} \cdot l_{cd}$				$-Fb^2/EJ$	
	totali				$2/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-2/5Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (2x/b - 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x^2/b - 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b + 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 1/2 x/b - 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/8 b) Fb 1/EJ = 5/8 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 1/2 x/b - x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/4 x^2/b - 1/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/4 b - 1/3 b + 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x/b + 1/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^2/b + 1/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b + 1/6 b - 1/8 b) Fb 1/EJ = 13/24 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-1/2Fx$	0	0	0	0
BA b	0	$1/2Fb-1/2Fx$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/12Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fb+1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	0	0
EF √5b	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} = L_{BE}$				Fb^2/EJ	
	totali				$7/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/5Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				1/3Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-1/5Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	0	0
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	11/12Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-5/2Fb+2Fx	5/2Fb-9/2Fx+2Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	1/2Fb+2Fx	1/2Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				10/3Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-2Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-1/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 3/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 9/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 9/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	0	0
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+2Fx	5/2Fb-9/2Fx+2Fx ² /b	1-2x/b+x ² /b ²	11/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+2Fx	1/2Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				4/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-4/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-1/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 3/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 9/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 9/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb	1/2Fb-1/2Fx	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb	1/2Fx	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}				Fb ² /EJ	
	totali				23/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-23/20Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b) Fb 1/EJ dx = [1/2 x - 1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b) Fb 1/EJ dx = [1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb	1/2Fb-1/2Fx	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb	1/2Fx	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ^ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				-1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b) Fb 1/EJ dx = [1/2 x - 1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b) Fb 1/EJ dx = [1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2qx ²	0	0	0	0
BA b	0	1/2Fb-Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} = L _{BE}				Fb ² /EJ	
	totali				7/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-7/5Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$





$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2qx ²	0	0	0	0
BA b	0	1/2Fb-Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ^ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				1/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-1/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb-3Fx$	$3Fb-3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-3Fb+5/2Fx$	$3Fb-11/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$13/12Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fb+5/2Fx$	$1/2Fx+5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} = L_{BE}$				Fb^2/EJ	
	totali				$11/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-11/5Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 11/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [3x - 11/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 11/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	3/2Fb ² /EJ	Xb/EJ
CD b	-1	-3Fx	3Fx	1	0	0
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+5/2Fx	3Fb-11/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+5/2Fx	1/2Fx+5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				5/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 11/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [3x - 11/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 11/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$





Schema di calcolo iperstatico




(+) M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M ₀ /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}				Fb ² /EJ	
	totali				7/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-7/5Fb	

Sviluppi di calcolo iperstatica

(+) M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fx-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-1/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



$M_0(x)$ flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x^2/b^2	$1/2 Fb^2 / EJ$	$1/3 Xb / EJ$
CB b	1-x/b	Fb	Fb-Fx	$1-2x/b+x^2/b^2$	$1/2 Fb^2 / EJ$	$1/3 Xb / EJ$
CD b	-1	-Fx	Fx	1	$1/2 Fb^2 / EJ$	Xb / EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2 Fb^2 / EJ$	Xb / EJ
DE b	-1+x/b	$-Fb+1/2qx^2$	$Fb-Fx-1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$11/24 Fb^2 / EJ$	$1/3 Xb / EJ$
ED b	x/b	$1/2Fb+Fx-1/2qx^2$	$1/2Fx+Fx^2/b-1/2qx^3/b$	x^2/b^2	$11/24 Fb^2 / EJ$	$1/3 Xb / EJ$
EF √5b	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} = L_{BE}$				Fb^2 / EJ	
	totali				$59/24 Fb^2 / EJ$	$5/3 Xb / EJ$
	iperstatica $X=W_{cd}$				-59/40 Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b - 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^2/b - 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b - 1/6 b + 1/8 b) Fb 1/EJ = 11/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/4 x^2/b + 1/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/3 b - 1/8 b) Fb 1/EJ = 11/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flexione da carichi assegnati



M_x flexione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x^2/b^2	$1/2 Fb^2 / EJ$	$1/3 Xb / EJ$
CB b	1-x/b	Fb	Fb-Fx	$1-2x/b+x^2/b^2$	$1/2 Fb^2 / EJ$	$1/3 Xb / EJ$
CD b	-1	-Fx	Fx	1	$1/2 Fb^2 / EJ$	Xb / EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2 Fb^2 / EJ$	Xb / EJ
DE b	-1+x/b	$-Fb+1/2qx^2$	$Fb-Fx-1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$11/24 Fb^2 / EJ$	$1/3 Xb / EJ$
ED b	x/b	$1/2Fb+Fx-1/2qx^2$	$1/2Fx+Fx^2/b-1/2qx^3/b$	x^2/b^2	$11/24 Fb^2 / EJ$	$1/3 Xb / EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2 / EJ$	
	totali				$11/24 Fb^2 / EJ$	$5/3 Xb / EJ$
	iperstatica $X=W_{cd}$				$-11/40 Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - x/b - 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 1/2 x^2/b - 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/2 b - 1/6 b + 1/8 b) Fb 1/EJ = 11/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/4 x^2/b + 1/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/3 b - 1/8 b) Fb 1/EJ = 11/24 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} -L _{BE}				Fb ² /EJ	
	totali				7/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-7/5Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$





Schema di calcolo iperstatico




(+) M₀ flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				1/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-1/5Fb	

Sviluppi di calcolo iperstatica

(+) M_x flessione da iperstatica X=1



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	$-3Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} L_{BE}$				Fb^2/EJ	
	totali				$19/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-19/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



(+) M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	5/4Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-5/2Fb+5/2Fx	5/2Fb-5Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	5/2Fx	5/2Fx ² /b	x ² /b ²	5/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				7/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-7/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$





Schema di calcolo iperstatico



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				7/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-21/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				-1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				3/20Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	1/2Fx-1/2qx ²	0	0	0	0
BA b	0	-1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}			0	Fb ² /EJ	
	totali				13/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-13/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	1/2Fx-1/2qx ²	0	0	0	0
BA b	0	-1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/3Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb+Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fx	Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}			0	-Fb ² /EJ	5/3Xb/EJ
	totali				1/6Fb ² /EJ	
	iperstatica X=W _{cd}				-1/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	$-2Fx+3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	1-x/b	Fb-3Fx	$Fb-4Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	0	0
CD b	-1	-3Fx	3Fx	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	3Fb-3Fx	$3Fb-3Fx$	1	0	0
DE b	-1+x/b	-3Fb+3Fx	$3Fb-6Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	3Fx	$3Fx^2/b$	x^2/b^2	0	0
EF √5b	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$			0	Fb^2/EJ	
	totali				$7/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-21/10Fb$	

Sviluppi di calcolo iperstatica



$(+)$ M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [-x^2/b + x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-b + b) \cdot Fb \cdot 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 2x^2/b + x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 2b + b) \cdot Fb \cdot 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) \cdot Fb \cdot 1/EJ \, dx = [3/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (3/2 b) \cdot Fb \cdot 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) \cdot Fb \cdot 1/EJ \, dx = [3x - 3/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$


$$= (3b - 3/2 b) \cdot Fb \cdot 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [3x - 3x^2/b + x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$


$$= (3b - 3b + b) \cdot Fb \cdot 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b) \cdot Fb \cdot 1/EJ = Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	$-2Fx+3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	1-x/b	Fb-3Fx	$Fb-4Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	0	0
CD b	-1	-3Fx	3Fx	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	$3Fb-6Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	3Fx	$3Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$4\sqrt{5}5Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$			0	$-Fb^2/EJ$	0
	totali				$3/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-9/10Fb$	0

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	-1+x/b	-Fb+Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-1/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$13/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/10Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = \left[x \right]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 \cdot b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = \left[x - \frac{1}{2} x^2/b \right]_0^b \cdot Fb \cdot 1/EJ$$


$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 \cdot Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[x - x^2/b + \frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$



$$= (b - b + 1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = \left[\frac{1}{3} x^3/b^2 \right]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/3 b) \cdot Fb \cdot 1/EJ = 1/3 \cdot Fb^2/EJ$$



Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fx^2/EJ$	$1/3Xb^2/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb^2/EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	-1+x/b	-Fb+Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb^2/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb^2/EJ$
EF √5b	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-1/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$1/6Fb^2/EJ$	$5/3Xb^2/EJ$
	iperstatica $X=W_{cd}$				$-1/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-1/2Fx$	0	0	0	0
BA b	0	$1/2Fb-1/2Fx$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+1/2Fx+1/2qx^2$	$Fb-3/2Fx+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fx-1/2qx^2$	$3/2Fx^2/b-1/2qx^3/b$	x^2/b^2	$3/8Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$55/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-11/8Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$


$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (b - 3/4 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-1/2Fx$	0	0	0	0
BA b	0	$1/2Fb-1/2Fx$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+1/2Fx+1/2qx^2$	$Fb-3/2Fx+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fx-1/2qx^2$	$3/2Fx^2/b-1/2qx^3/b$	x^2/b^2	$3/8Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$7/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/40Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (3/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	0	0
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+2Fx	5/2Fb-9/2Fx+2Fx ² /b	1-2x/b+x ² /b ²	11/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+2Fx	1/2Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} L_{BE}$				Fb ² /EJ	
	totali				10/3Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-2Fb	

Sviluppi di calcolo iperstatica

(+) M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-1/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 3/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 5/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$



$$= (5/2 b - 5/4 b) \cdot Fb \cdot 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [5/2 x - 9/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (5/2 b - 9/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/4 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/4 b + 2/3 b) \cdot Fb \cdot 1/EJ = 11/12 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	0	0
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+2Fx	5/2Fb-9/2Fx+2Fx ² /b	1-2x/b+x ² /b ²	11/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+2Fx	1/2Fx+2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				4/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-4/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 2x^2/b^2) Fb 1/EJ dx = [5/2 x - 9/4 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 9/4 b + 2/3 b) Fb 1/EJ = 11/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 2x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/4 b + 2/3 b) Fb 1/EJ = 11/12 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1		
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	$-3Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon_{BE}} L_{BE}$				Fb^2/EJ	
	totali				$19/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-19/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1		
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	$-3Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \cdot \epsilon_{cd} \cdot L_{cd}$				$-Fb^2/EJ$	
	totali				$7/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/10Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3/2Fx-1/2qx ²	3/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DC b	1	2Fb-5/2Fx+1/2qx ²	2Fb-5/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-2Fb+2Fx	2Fb-4Fx+2Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	2Fx	2Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				11/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-33/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/6 b) Fb 1/EJ = 11/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (2b - 5/4 b + 1/6 b) Fb 1/EJ = 11/12 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (2 - 4x/b + 2x^2/b^2) Fb 1/EJ dx = [2x - 2x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2b - 2b + 2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (2x^2/b^2) Fb 1/EJ dx = [2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M ₀ /EJdx
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3/2Fx-1/2qx ²	3/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DC b	1	2Fb-5/2Fx+1/2qx ²	2Fb-5/2Fx+1/2Fx ² /b	1	2/3Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-2Fb+2Fx	2Fb-4Fx+2Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	2Fx	2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				3/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-9/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (-1/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 3/2 b + 2/3 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= [3/4 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= (3/4 b + 1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$

$$= [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ$$



$$= (2b - 5/4 b + 1/6 b) \cdot Fb \cdot 1/EJ + 1 \cdot (-1) \cdot 1 \cdot Fb^2/EJ = -1/12 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (2 - 4x/b + 2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [2x - 2x^2/b + 2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (2b - 2b + 2/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (2x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [2/3 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (2/3 b) \cdot Fb \cdot 1/EJ = 2/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-3/2Fb + Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$3/2Fb - 5/2Fx$	$-3/2Fx + 5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 5/2Fx$	$Fb - 7/2Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	0	0
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	0	0
DE b	$-1+x/b$	$-5/2Fb + 5/2Fx$	$5/2Fb - 5Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	$5/3Xb/EJ$
	totali				$19/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				-19/10Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-3/2Fb + Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$3/2Fb - 5/2Fx$	$-3/2Fx + 5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 5/2Fx$	$Fb - 7/2Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	0	0
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DE b	$-1+x/b$	$-5/2Fb + 5/2Fx$	$5/2Fb - 5Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	0	0
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$7/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$7/2Fx$	0	0	0	0
BA b	0	$-7/2Fb+7/2Fx$	0	0	0	0
BC b	$-x/b$	$7/2Fb-9/2Fx$	$-7/2Fx+9/2Fx^2/b$	x^2/b^2	$-1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-9/2Fx$	$Fb-11/2Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$9/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-9/2Fx$	$9/2Fx$	1	0	0
DC b	1	$9/2Fb-9/2Fx$	$9/2Fb-9/2Fx$	1	0	0
DE b	$-1+x/b$	$-9/2Fb+9/2Fx$	$9/2Fb-9Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$9/2Fx$	$9/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$11\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$8Fb-3Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-5Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^E L_{BE}^{E-BE}$				Fb^2/EJ	$5/3Xb/EJ$
	totali				$9/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-27/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-7/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [-7/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-7/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 11/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [x - 11/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 11/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx = [9/4 x^2/b]_0^b Fb 1/EJ$$

$$= (9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ$$



$$= (9/2 b - 9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (9/2 - 9x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 9/2 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 9/2 b + 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (9/2 x^2/b^2) Fb 1/EJ dx = [3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$7/2Fx$	0	0	0	0
BA b	0	$-7/2Fb+7/2Fx$	0	0	0	0
BC b	$-x/b$	$7/2Fb-9/2Fx$	$-7/2Fx+9/2Fx^2/b$	x^2/b^2	$-1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-9/2Fx$	$Fb-11/2Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$9/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-9/2Fx$	$9/2Fx$	1	0	0
DC b	1	$9/2Fb-9/2Fx$	$9/2Fb-9/2Fx$	1	0	0
DE b	$-1+x/b$	$-9/2Fb+9/2Fx$	$9/2Fb-9Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$9/2Fx$	$9/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$11\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$8Fb-3Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-5Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$5/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-3/2Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-7/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [-7/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-7/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 11/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [x - 11/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 11/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/2 b - 9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (9/2 - 9x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 9/2 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 9/2 b + 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (9/2 x^2/b^2) Fb 1/EJ dx = [3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/6Fb ² /EJ	1/3Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+5/2Fx	5/2Fb-5Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	5/2Fx	5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	5/3Xb/EJ
	totali				7/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-7/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0		
BC b	-x/b	Fb-2Fx	$-Fx+2Fx^2/b$	x^2/b^2	$1/6Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-2Fx	$Fb-3Fx+2Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	$5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1		
DE b	$-1+x/b$	$-5/2Fb+2Fx+1/2qx^2$	$5/2Fb-9/2Fx+3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$7/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3Fx-1/2qx^2$	$3Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0		
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0		
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$79/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-79/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$

$$= [5/2 x - 9/4 x^2/b + 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (5/2 b - 9/4 b + 1/2 b + 1/8 b) Fb 1/EJ = 7/8 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$


$$= (b - 1/8 b) Fb 1/EJ = 7/8 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_1 flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0		
BC b	-x/b	Fb-2Fx	$-Fx+2Fx^2/b$	x^2/b^2	$1/6Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-2Fx	$Fb-3Fx+2Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	-5/2Fx	5/2Fx	1	$5/4Fb^2/EJ$	Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1		
DE b	-1+x/b	$-5/2Fb+2Fx+1/2qx^2$	$5/2Fb-9/2Fx+3/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$7/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3Fx-1/2qx^2$	$3Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0		
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0		
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$31/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-31/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (5/2 - 9/2 x/b + 3/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$


$$= [5/2 x - 9/4 x^2/b + 1/2 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (5/2 b - 9/4 b + 1/2 b + 1/8 b) Fb 1/EJ = 7/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 1/8 b) Fb 1/EJ = 7/8 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb	1/2Fb-1/2Fx	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb	1/2Fx	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta N _{1, BE} = ε _{BE} L _{BE}				Fb ² /EJ	
	totali				23/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-23/20Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) \cdot 1/EJ \, dx = [x]_0^b \cdot 1/EJ$$

$$= (b) \cdot 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) \cdot 1/EJ \, dx = [x - x^2/b + 1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (b - b + 1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) \cdot 1/EJ \, dx = [1/3 x^3/b^2]_0^b \cdot 1/EJ$$

$$= (1/3 b) \cdot 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) \cdot Fb \cdot 1/EJ \, dx = [x - 1/2 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (b - 1/2 b) \cdot Fb \cdot 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b \cdot Fb \cdot 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) \cdot Fb \cdot 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [1/2 x - 1/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/2 b - 1/4 b) \cdot Fb \cdot 1/EJ = 1/4 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b) \cdot Fb \cdot 1/EJ \, dx = [1/4 x^2/b]_0^b \cdot Fb \cdot 1/EJ$$

$$= (1/4 b) \cdot Fb \cdot 1/EJ = 1/4 Fb^2/EJ$$






Schema di calcolo iperstatico



M₀ flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0	0	0
BC b	-x/b	-Fb	Fx	x ² /b ²	1/2Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb	Fb-Fx	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb	1/2Fb-1/2Fx	1-2x/b+x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb	1/2Fx	x ² /b ²	1/4Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta N _{1,CD} ^ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				-1/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				1/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b) Fb 1/EJ dx = [1/2 x - 1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x/b) Fb 1/EJ dx = [1/4 x^2/b]_0^b Fb 1/EJ$$

$$= (1/4 b) Fb 1/EJ = 1/4 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				7/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-21/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				-1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				3/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3/2Fx-1/2qx ²	3/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DC b	1	2Fb-5/2Fx+1/2qx ²	2Fb-5/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-2Fb+2Fx	2Fb-4Fx+2Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	2Fx	2Fx ² /b	x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				11/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-33/20Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/4 b + 1/6 b) Fb 1/EJ = 11/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (2b - 5/4 b + 1/6 b) Fb 1/EJ = 11/12 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (2 - 4x/b + 2x^2/b^2) Fb 1/EJ dx = [2x - 2x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$



$$= (2b - 2b + 2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (2x^2/b^2) Fb 1/EJ dx = [2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$



Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M ₀ /EJdx
AB b	0	Fx	0	0	0	0
BA b	0	-Fb+Fx	0	0	0	0
BC b	-x/b	Fb-2Fx	-Fx+2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-2Fx	Fb-3Fx+2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
CD b	-1	-3/2Fx-1/2qx ²	3/2Fx+1/2Fx ² /b	1	11/12Fb ² /EJ	Xb/EJ
DC b	1	2Fb-5/2Fx+1/2qx ²	2Fb-5/2Fx+1/2Fx ² /b	1	2/3Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-2Fb+2Fx	2Fb-4Fx+2Fx ² /b	1-2x/b+x ² /b ²	2/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	2Fx	2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				3/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-9/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-x/b + 2x^2/b^2) Fb 1/EJ dx = [-1/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-1/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3x/b + 2x^2/b^2) Fb 1/EJ dx = [x - 3/2 x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/2 b + 2/3 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/4 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/12 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (2 - 5/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [2x - 5/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (2b - 5/4 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/12 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (2 - 4x/b + 2x^2/b^2) Fb 1/EJ dx = [2x - 2x^2/b + 2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2b - 2b + 2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (2x^2/b^2) Fb 1/EJ dx = [2/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (2/3 b) Fb 1/EJ = 2/3 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$-1/2qx^2$	0	0	0	0
BA b	0	$1/2Fb-Fx+1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/6Fb^2/EJ$	Xb/EJ
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-1/2Fb+1/2Fx$	$1/2Fb-Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fx$	$1/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$7/4Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-21/20Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico



M_x , flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$-1/2qx^2$	0	0	0	0
BA b	0	$1/2Fb-Fx+1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb+1/2Fx$	$1/2Fb-Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fx$	$1/2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$-1/4Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$3/20Fb$	

Sviluppi di calcolo iperstatica

M_x , flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	Xb/EJ
CD b	-1	-2Fx-1/2qx ²	2Fx+1/2Fx ² /b	1	5/6Fb ² /EJ	1/3Xb/EJ
DC b	1	5/2Fb-3Fx+1/2qx ²	5/2Fb-3Fx+1/2Fx ² /b	1	5/6Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-5/2Fb+5/2Fx	5/2Fb-5Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	5/2Fx	5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^{\epsilon} L_{BE}$				Fb ² /EJ	
	totali				37/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-37/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	7/6Fb ² /EJ	Xb/EJ
CD b	-1	-2Fx-1/2qx ²	2Fx+1/2Fx ² /b	1	0	0
DC b	1	5/2Fb-3Fx+1/2qx ²	5/2Fb-3Fx+1/2Fx ² /b	1	0	0
DE b	-1+x/b	-5/2Fb+5/2Fx	5/2Fb-5Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	5/2Fx	5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				13/12Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-13/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				7/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-21/20Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				-1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				3/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_x , flessione da iperstatica X=1



M_0 , flessione da carichi assegnati

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0		
BC b	-x/b	-Fb	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb	Fb-Fx	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb+1/2qx^2$	$1/2Fb-1/2Fx-1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$5/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fx-1/2qx^2$	$Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0		
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$15/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$-9/8Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b - 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$


$$= [1/2 x - 1/4 x^2/b - 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/4 b - 1/6 b + 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/3 b - 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-Fx	0	0	0	0
BA b	0	Fb-Fx	0	0		
BC b	-x/b	-Fb	Fx	x^2/b^2	$1/2Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb	Fb-Fx	$1-2x/b+x^2/b^2$		
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-1/2Fb+1/2qx^2$	$1/2Fb-1/2Fx-1/2Fx^2/b+1/2qx^3/b$	$1-2x/b+x^2/b^2$	$5/24Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$Fx-1/2qx^2$	$Fx^2/b-1/2qx^3/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0		
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0		
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
CD	elongazione asta $N_{1CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$-1/8Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$3/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$



$$L_{DE}^{xo} = \int_0^b (1/2 - 1/2 x/b - 1/2 x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx$$

$$= [1/2 x - 1/4 x^2/b - 1/6 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/4 b - 1/6 b + 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/3 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/3 b - 1/8 b) Fb 1/EJ = 5/24 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$





$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$



Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	1/2Fx-1/2qx ²	0	0	0	0
BA b	0	-1/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-Fx	Fx ² /b	x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/3Fb ² /EJ	1/3Xb/EJ
DE b	-1+x/b	-Fb+Fx	Fb-2Fx+Fx ² /b	1-2x/b+x ² /b ²	1/3Fb ² /EJ	1/3Xb/EJ
ED b	x/b	Fx	Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				13/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-13/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fx$	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$1/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-1/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$


$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-3/2Fb + Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$3/2Fb - 5/2Fx$	$-3/2Fx + 5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 5/2Fx$	$Fb - 7/2Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	$5/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-5/2Fb + 5/2Fx$	$5/2Fb - 5Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	$5/6Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	$5/3Xb/EJ$
	totali				$19/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-19/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-3/2Fb + Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$3/2Fb - 5/2Fx$	$-3/2Fx + 5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 5/2Fx$	$Fb - 7/2Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DC b	1	$5/2Fb - 5/2Fx$	$5/2Fb - 5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DE b	$-1+x/b$	$-5/2Fb + 5/2Fx$	$5/2Fb - 5Fx + 5/2Fx^2/b$	$1 - 2x/b + x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx + 1/2qx^2$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$6Fb - 3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \cdot \epsilon_{cd} \cdot L_{cd}$				$-Fb^2/EJ$	
	totali				$7/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2qx ²	0	0	0	0
BA b	0	1/2Fb-Fx+1/2qx ²	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} L _{BE}				Fb ² /EJ	
	totali				7/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-21/20Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{CD}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$-1/2qx^2$	0	0	0	0
BA b	0	$1/2Fb-Fx+1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/6Fb^2/EJ$	Xb/EJ
CD b	-1	$-1/2qx^2$	$1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DC b	1	$1/2Fb-Fx+1/2qx^2$	$1/2Fb-Fx+1/2Fx^2/b$	1	$1/6Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-1/2Fb+1/2Fx$	$1/2Fb-Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fx$	$1/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,CD} \epsilon_{CD} L_{CD}$				$-Fb^2/EJ$	
	totali				$-1/4Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{CD}$				$3/20Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$5/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-2Fb + 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	-x/b	$2Fb - 3Fx$	$-2Fx + 3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 3Fx$	$Fb - 4Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	0	Xb/EJ
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb - 3Fx$	$3Fb - 3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-3Fb + 3Fx$	$3Fb - 6Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	$3Fx$	$3Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF √5b	0	$4\sqrt{5}5Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb - Fx - 1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx + 1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$7/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-21/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	5/2Fx-1/2qx ²	0	0	0	0
BA b	0	-2Fb+3/2Fx+1/2qx ²	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	0
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-9/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1		
DC b	1	Fb-Fx	Fb-Fx	1		
DE b	$-1+x/b$	-Fb+Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2		
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-5/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$2Fb-3/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$13/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica X=W _{cd}				$-13/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fx$	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-5/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$2Fb - 3/2Fx - 1/2qx^2$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$1/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-1/10Fb$	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-1/2qx^2$	0	0	0	0
BA b	0	$1/2Fb-Fx+1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+1/2Fx+1/2qx^2$	$Fb-3/2Fx+1/2qx^2/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fx-1/2qx^2$	$3/2Fx^2/b-1/2qx^3/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^E - N_{BE}^E - N_{BE}^E$				Fb^2/EJ	
	totali				$55/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-11/8Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$-1/2qx^2$	0	0	0	0
BA b	0	$1/2Fb-Fx+1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-1/2Fb-1/2Fx$	$1/2Fx+1/2Fx^2/b$	x^2/b^2	$5/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-1/2Fx$	$Fb-3/2Fx+1/2Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+1/2Fx+1/2qx^2$	$Fb-3/2Fx+1/2qx^2/b$	$1-2x/b+x^2/b^2$	$3/8Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$3/2Fx-1/2qx^2$	$3/2Fx^2/b-1/2qx^3/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \cdot l_{cd} \cdot L_{cd}$				$-Fb^2/EJ$	
	totali				$7/24Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-7/40Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^3/b^3) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [1/2 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/8 b) Fb 1/EJ = 3/8 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contributi PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	3/2Fb ² /EJ	Xb/EJ
CD b	-1	-3Fx	3Fx	1	0	0
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+5/2Fx	3Fb-11/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	13/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+5/2Fx	1/2Fx+5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} = L_{BE}$				Fb ² /EJ	
	totali				11/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-11/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 11/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [3x - 11/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 11/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$





Schema di calcolo iperstatico



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-3Fx$	$3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb-3Fx$	$3Fb-3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-3Fb+5/2Fx$	$3Fb-11/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$13/12Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$1/2Fb+5/2Fx$	$1/2Fx+5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	$Fx-1/2qx^2$	0	0	0	0
EB b	0	$-1/2Fb+1/2qx^2$	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$5/3Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 11/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [3x - 11/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 11/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 5/6 b) Fb 1/EJ = 13/12 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int X M_x M_x / E J dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	0
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	Fb-1/2qx ²	0	0	0	0
AG 2b	0	Fb-2Fx+1/2qx ²	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-21/10Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	$-2Fx+3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	1-x/b	Fb-3Fx	$Fb-4Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	0	0
CD b	-1	-3Fx	3Fx	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	$3Fb-6Fx+3Fx^2/b$	$1-2x/b+x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	3Fx	$3Fx^2/b$	x^2/b^2	0	0
EF √5b	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	0	0	0	0	0
GF b	0	0	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,CD} \epsilon_{CD} L_{CD}$			0	$-Fb^2/EJ$	0
	totali				$3/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica X=W _{CD}				$-9/10Fb$	0

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica X=1

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$7/2Fx$	0	0	0	0
BA b	0	$-7/2Fb+7/2Fx$	0	0	0	0
BC b	$-x/b$	$7/2Fb-9/2Fx$	$-7/2Fx+9/2Fx^2/b$	x^2/b^2	$-1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-9/2Fx$	$Fb-11/2Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$9/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-9/2Fx$	$9/2Fx$	1	0	0
DC b	1	$9/2Fb-9/2Fx$	$9/2Fb-9/2Fx$	1	0	0
DE b	$-1+x/b$	$-9/2Fb+9/2Fx$	$9/2Fb-9Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$9/2Fx$	$9/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$11\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$8Fb-3Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-5Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE}^E - N_{1, BE}^L - N_{1, BE}^B$				Fb^2/EJ	$5/3Xb/EJ$
	totali				$9/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-27/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-7/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [-7/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-7/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 11/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [x - 11/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 11/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx = [9/4 x^2/b]_0^b Fb 1/EJ$$

$$= (9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ$$



$$= (9/2 b - 9/4 b) Fb 1/EJ = 9/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (9/2 - 9x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 9/2 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 9/2 b + 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (9/2 x^2/b^2) Fb 1/EJ dx = [3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M_0 flessione da carichi assegnati



(+) M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$7/2Fx$	0	0	0	0
BA b	0	$-7/2Fb+7/2Fx$	0	0	0	0
BC b	$-x/b$	$7/2Fb-9/2Fx$	$-7/2Fx+9/2Fx^2/b$	x^2/b^2	$-1/4Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-9/2Fx$	$Fb-11/2Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$-1/4Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	$-9/2Fx$	$9/2Fx$	1	$9/4Fb^2/EJ$	Xb/EJ
DC b	1	$9/2Fb-9/2Fx$	$9/2Fb-9/2Fx$	1	$9/4Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-9/2Fb+9/2Fx$	$9/2Fb-9Fx+9/2Fx^2/b$	$1-2x/b+x^2/b^2$	$3/2Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$9/2Fx$	$9/2Fx^2/b$	x^2/b^2	$3/2Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$11\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$8Fb-3Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-5Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$5/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-3/2Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-7/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [-7/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-7/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 11/2 x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [x - 11/4 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 11/4 b + 3/2 b) Fb 1/EJ = -1/4 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (9/2 - 9/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [9/2 x - 9/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (9/2 b - 9/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (9/2 - 9x/b + 9/2 x^2/b^2) Fb 1/EJ dx = [9/2 x - 9/2 x^2/b + 3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (9/2 b - 9/2 b + 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (9/2 x^2/b^2) Fb 1/EJ dx = [3/2 x^3/b^2]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$7/6Fb^2/EJ$	Xb/EJ
CD b	-1	$-2Fx-1/2qx^2$	$2Fx+1/2Fx^2/b$	1		
DC b	1	$5/2Fb-3Fx+1/2qx^2$	$5/2Fb-3Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$37/12Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-37/20Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ = 7/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$


$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$7/6Fb^2/EJ$	Xb/EJ
CD b	-1	$-2Fx-1/2qx^2$	$2Fx+1/2Fx^2/b$	1		
DC b	1	$5/2Fb-3Fx+1/2qx^2$	$5/2Fb-3Fx+1/2Fx^2/b$	1		
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/6Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2		
EF $\sqrt{5}b$	0	$4\sqrt{5}Fx$	0	0	0	0
FG b	0	$-2Fx$	0	0	0	0
GF b	0	$2Fb-2Fx$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb-Fx-1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx+1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$13/12Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/20Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (2x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 3x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [5/2 x - 3/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (5/2 b - 3/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/6 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



Schema di calcolo iperstatico



Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$5/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-2Fb + 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$2Fb - 3Fx$	$-2Fx + 3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 3Fx$	$Fb - 4Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb - 3Fx$	$3Fb - 3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1 + x/b$	$-3Fb + 3Fx$	$3Fb - 6Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	3Fx	$3Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$4\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb - Fx - 1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx + 1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$7/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-21/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$


$$= (b) Fb 1/EJ = Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	$5/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-2Fb + 3/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$2Fb - 3Fx$	$-2Fx + 3Fx^2/b$	x^2/b^2	0	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb - 3Fx$	$Fb - 4Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	$3/2Fb^2/EJ$	Xb/EJ
DC b	1	$3Fb - 3Fx$	$3Fb - 3Fx$	1	$3/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-3Fb + 3Fx$	$3Fb - 6Fx + 3Fx^2/b$	$1 - 2x/b + x^2/b^2$	Fb^2/EJ	$1/3Xb/EJ$
ED b	x/b	3Fx	$3Fx^2/b$	x^2/b^2	Fb^2/EJ	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$4\sqrt{5}/5Fx$	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	$2Fb - 2Fx$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$4Fb - Fx - 1/2qx^2$	0	0	0	0
BF 2b	0	$-3Fx + 1/2qx^2$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$3/2Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-9/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$


$$= (b) Fb 1/EJ = Fb^2/EJ$$



Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica $X=1$

Quadro contributi PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	Fb ² /EJ	1/3Xb/EJ
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-21/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$


$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$


$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$




Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-9/10Fb	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$



Quadro contributi PLV per iperstatica $X=W_{CD}$

→	$M_x(x)$	$M_o(x)$	$M_x M_o$	$M_x M_x$	$\int M_x M_o / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0		
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²		
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1		
DE b	-1+x/b	-3Fb+5/2Fx+1/2qx ²	3Fb-11/2Fx+2Fx ² /b+1/2qx ³ /b	1-2x/b+x ² /b ²	25/24Fb ² /EJ	1/3Xb/EJ
ED b	x/b	7/2Fx-1/2qx ²	7/2Fx ² /b-1/2qx ³ /b	x ² /b ²		
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-2Fx	0	0	0	0
GF b	0	2Fb-2Fx	0	0		
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0		
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0		
BE b	0	0	0	0	0	0
EB b	0	0	0	0		
BE	elongazione asta $N_{1BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				29/8Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{CD}$				-87/40Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 11/2 x/b + 2x^2/b^2 + 1/2 x^3/b^3) Fb 1/EJ dx = [3x - 11/4 x^2/b + 2/3 x^3/b^2 + 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (3b - 11/4 b + 2/3 b + 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (7/2 x^2/b^2 - 1/2 x^3/b^3) Fb 1/EJ dx = [7/6 x^3/b^2 - 1/8 x^4/b^3]_0^b Fb 1/EJ$$

$$= (7/6 b - 1/8 b) Fb 1/EJ = 25/24 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{CD}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				7/3Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				-7/5Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M_0 flessione da carichi assegnati



(+) M_x flessione da iperstatica $X=1$

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/2Fb ² /EJ	Xb/EJ
CD b	-1	-Fx	Fx	1	1/2Fb ² /EJ	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	1/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-Fb+1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fb+1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	Fx-1/2qx ²	0	0	0	0
EB b	0	-1/2Fb+1/2qx ²	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				1/3Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-1/5Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	-1+x/b	-Fb+Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF √5b	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-1/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$13/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-13/10Fb$	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int X M_x M_x / EJ dx$
AB b	0	0	0	0	0	0
BA b	0	0	0	0	0	0
BC b	-x/b	-Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	1-x/b	Fb-Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	-Fx	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	Fb-Fx	Fb-Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	-1+x/b	-Fb+Fx	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF √5b	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-1/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$1/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$Fb-1/2qx^2$	0	0	0	0
AG 2b	0	$Fb-2Fx+1/2qx^2$	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$1/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-1/10Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	$3/2Fx$	0	0	0	0
BA b	0	$-3/2Fb+3/2Fx$	0	0	0	0
BC b	$-x/b$	$3/2Fb-5/2Fx$	$-3/2Fx+5/2Fx^2/b$	x^2/b^2	$1/12Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-5/2Fx$	$Fb-7/2Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	$5/4Fb^2/EJ$	Xb/EJ
CD b	-1	$-5/2Fx$	$5/2Fx$	1	$5/6Fb^2/EJ$	$1/3Xb/EJ$
DC b	1	$5/2Fb-5/2Fx$	$5/2Fb-5/2Fx$	1	0	0
DE b	$-1+x/b$	$-5/2Fb+5/2Fx$	$5/2Fb-5Fx+5/2Fx^2/b$	$1-2x/b+x^2/b^2$	0	0
ED b	x/b	$5/2Fx$	$5/2Fx^2/b$	x^2/b^2	0	0
EF $\sqrt{5}b$	0	$7\sqrt{5}/10Fx+1/2qx^2$	0	0	0	0
FG b	0	$-5/2Fx+1/2qx^2$	0	0	0	0
GF b	0	$2Fb-3/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$6Fb-3Fx$	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$19/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-19/10Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx = [5/4 x^2/b]_0^b Fb 1/EJ$$

$$= (5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ = 5/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫M _x M _x /EJdx
AB b	0	3/2Fx	0	0	0	0
BA b	0	-3/2Fb+3/2Fx	0	0	0	0
BC b	-x/b	3/2Fb-5/2Fx	-3/2Fx+5/2Fx ² /b	x ² /b ²	1/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-5/2Fx	Fb-7/2Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	5/4Fb ² /EJ	Xb/EJ
CD b	-1	-5/2Fx	5/2Fx	1	5/6Fb ² /EJ	1/3Xb/EJ
DC b	1	5/2Fb-5/2Fx	5/2Fb-5/2Fx	1	0	0
DE b	-1+x/b	-5/2Fb+5/2Fx	5/2Fb-5Fx+5/2Fx ² /b	1-2x/b+x ² /b ²	0	0
ED b	x/b	5/2Fx	5/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	7√5/10Fx+1/2qx ²	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	6Fb-3Fx	0	0	0	0
BF 2b	0	-3Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,cd} ε _{cd} L _{cd}				-Fb ² /EJ	5/3Xb/EJ
	totali				7/6Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-7/10Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-3/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [-3/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (-3/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 7/2 x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [x - 7/4 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 7/4 b + 5/6 b) Fb 1/EJ = 1/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (5/2 - 5/2 x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [5/2 x - 5/4 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (5/2 b - 5/4 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/4 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (5/2 - 5x/b + 5/2 x^2/b^2) Fb 1/EJ dx = [5/2 x - 5/2 x^2/b + 5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/2 b - 5/2 b + 5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$



$$L_{ED}^{xo} = \int_0^b (5/2 x^2/b^2) Fb 1/EJ dx = [5/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (5/6 b) Fb 1/EJ = 5/6 Fb^2/EJ$$





Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica X=W_{cd}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	0	0
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta N _{1, BE} ε _{BE} l _{BE}				Fb ² /EJ	
	totali				7/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{cd}				-21/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



(+) M₀ flessione da carichi assegnati



(+) M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{CD}

→	M _x (x)	M ₀ (x)	M _x M ₀	M _x M _x	∫M _x M ₀ /EJdx	∫XM _x M _x /EJdx
AB b	0	-1/2Fx	0	0	0	0
BA b	0	1/2Fb-1/2Fx	0	0	0	0
BC b	-x/b	-1/2Fb-1/2Fx	1/2Fx+1/2Fx ² /b	x ² /b ²	5/12Fb ² /EJ	1/3Xb/EJ
CB b	1-x/b	Fb-1/2Fx	Fb-3/2Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	Xb/EJ
CD b	-1	-1/2qx ²	1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DC b	1	1/2Fb-Fx+1/2qx ²	1/2Fb-Fx+1/2Fx ² /b	1	1/6Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-1/2Fb+1/2Fx	1/2Fb-Fx+1/2Fx ² /b	1-2x/b+x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
ED b	x/b	1/2Fx	1/2Fx ² /b	x ² /b ²	1/6Fb ² /EJ	1/3Xb/EJ
EF √5b	0	2√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	2Fb-Fx	0	0	0	0
BF 2b	0	-Fx	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta N _{1,CD} ε _{CD} L _{CD}				-Fb ² /EJ	
	totali				-1/4Fb ² /EJ	5/3Xb/EJ
	iperstatica X=W _{CD}				3/20Fb	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (1/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 3/2 x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [x - 3/4 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 3/4 b + 1/6 b) Fb 1/EJ = 5/12 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ$$

$$= [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -5/6 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1/2 - x/b + 1/2 x^2/b^2) Fb 1/EJ dx = [1/2 x - 1/2 x^2/b + 1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/2 b - 1/2 b + 1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (1/2 x^2/b^2) Fb 1/EJ dx = [1/6 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/6 b) Fb 1/EJ = 1/6 Fb^2/EJ$$






Schema di calcolo iperstatico



M_0 flessione da carichi assegnati



M_x flessione da iperstatica X=1

Quadro contribuiti PLV per iperstatica X=W_{cd}

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fx$	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-5/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$2Fb-3/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb^2/EJ	
	totali				$13/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica X=W _{cd}				$-13/10Fb$	

Sviluppi di calcolo iperstatica

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx = [1/2 x^2/b]_0^b Fb 1/EJ$$

$$= (1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx = [x - 1/2 x^2/b]_0^b Fb 1/EJ$$



$$= (b - 1/2 b) Fb 1/EJ = 1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

\rightarrow	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / E J dx$	$\int M_x M_x / E J dx$
AB b	0	$1/2Fx - 1/2qx^2$	0	0	0	0
BA b	0	$-1/2Fx + 1/2qx^2$	0	0	0	0
BC b	$-x/b$	$-Fx$	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
CB b	$1-x/b$	$Fb-Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/2Fb^2/EJ$	Xb/EJ
CD b	-1	$-Fx$	Fx	1	$1/2Fb^2/EJ$	Xb/EJ
DC b	1	$Fb-Fx$	$Fb-Fx$	1	$1/2Fb^2/EJ$	Xb/EJ
DE b	$-1+x/b$	$-Fb+Fx$	$Fb-2Fx+Fx^2/b$	$1-2x/b+x^2/b^2$	$1/3Fb^2/EJ$	$1/3Xb/EJ$
ED b	x/b	Fx	Fx^2/b	x^2/b^2	$1/3Fb^2/EJ$	$1/3Xb/EJ$
EF $\sqrt{5}b$	0	$2\sqrt{5}Fx$	0	0	0	0
FG b	0	$-5/2Fx + 1/2qx^2$	0	0	0	0
GF b	0	$2Fb-3/2Fx-1/2qx^2$	0	0	0	0
GA 2b	0	$-Fb$	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	$2Fb-Fx$	0	0	0	0
BF 2b	0	$-Fx$	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				$-Fb^2/EJ$	
	totali				$1/6Fb^2/EJ$	$5/3Xb/EJ$
	iperstatica $X=W_{cd}$				$-1/10Fb$	

Sviluppi di calcolo iperstatica



M_x flessione da iperstatica $X=1$

$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CB}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$

$$L_{CD}^{xo} = \int_0^b (x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (1 - x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [x - 1/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$



$$= (b - 1/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = -1/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (1 - 2x/b + x^2/b^2) Fb 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - b + 1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (x^2/b^2) Fb 1/EJ dx = [1/3 x^3/b^2]_0^b Fb 1/EJ$$

$$= (1/3 b) Fb 1/EJ = 1/3 Fb^2/EJ$$






Schema di calcolo iperstatico



Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	0	0
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
BE	elongazione asta $N_{1, BE} \epsilon_{BE} L_{BE}$				Fb ² /EJ	
	totali				7/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-21/10Fb	

Sviluppi di calcolo iperstatica



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx = [3/2 x^2/b]_0^b Fb 1/EJ$$

$$= (3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx = [3x - 3/2 x^2/b]_0^b Fb 1/EJ$$



$$= (3b - 3/2 b) Fb 1/EJ = 3/2 Fb^2/EJ$$


$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$


$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$





Schema di calcolo iperstatico




M_0 flessione da carichi assegnati

Quadro contribuiti PLV per iperstatica $X=W_{cd}$

→	$M_x(x)$	$M_0(x)$	$M_x M_0$	$M_x M_x$	$\int M_x M_0 / EJ dx$	$\int M_x M_x / EJ dx$
AB b	0	2Fx	0	0	0	0
BA b	0	-2Fb+2Fx	0	0	0	0
BC b	-x/b	2Fb-3Fx	-2Fx+3Fx ² /b	x ² /b ²	0	1/3Xb/EJ
CB b	1-x/b	Fb-3Fx	Fb-4Fx+3Fx ² /b	1-2x/b+x ² /b ²	0	Xb/EJ
CD b	-1	-3Fx	3Fx	1	3/2Fb ² /EJ	Xb/EJ
DC b	1	3Fb-3Fx	3Fb-3Fx	1	3/2Fb ² /EJ	Xb/EJ
DE b	-1+x/b	-3Fb+3Fx	3Fb-6Fx+3Fx ² /b	1-2x/b+x ² /b ²	Fb ² /EJ	1/3Xb/EJ
ED b	x/b	3Fx	3Fx ² /b	x ² /b ²	0	0
EF √5b	0	4√5/5Fx	0	0	0	0
FG b	0	-5/2Fx+1/2qx ²	0	0	0	0
GF b	0	2Fb-3/2Fx-1/2qx ²	0	0	0	0
GA 2b	0	-Fb	0	0	0	0
AG 2b	0	Fb	0	0	0	0
FB 2b	0	4Fb-Fx-1/2qx ²	0	0	0	0
BF 2b	0	-3Fx+1/2qx ²	0	0	0	0
BE b	0	0	0	0	0	0
EB b	0	0	0	0	0	0
CD	elongazione asta $N_{1,cd} \epsilon_{cd} L_{cd}$				-Fb ² /EJ	
	totali				3/2Fb ² /EJ	5/3Xb/EJ
	iperstatica $X=W_{cd}$				-9/10Fb	

Sviluppi di calcolo iperstatica

M_x flessione da iperstatica $X=1$



$$L_{BC}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CB}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{CD}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DC}^{xx} = \int_0^b (1) 1/EJ dx = [x]_0^b 1/EJ$$

$$= (b) 1/EJ = b/EJ$$

$$L_{DE}^{xx} = \int_0^b (1 - 2x/b + x^2/b^2) 1/EJ dx = [x - x^2/b + 1/3 x^3/b^2]_0^b 1/EJ$$

$$= (b - b + 1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{ED}^{xx} = \int_0^b (x^2/b^2) 1/EJ dx = [1/3 x^3/b^2]_0^b 1/EJ$$

$$= (1/3 b) 1/EJ = 1/3 b/EJ$$

$$L_{BC}^{xo} = \int_0^b (-2x/b + 3x^2/b^2) Fb 1/EJ dx = [-x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (-b + b) Fb 1/EJ = 0$$

$$L_{CB}^{xo} = \int_0^b (1 - 4x/b + 3x^2/b^2) Fb 1/EJ dx = [x - 2x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (b - 2b + b) Fb 1/EJ = 0$$

$$L_{CD}^{xo} = \int_0^b (3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DC}^{xo} = \int_0^b (3 - 3x/b) Fb 1/EJ dx + 1 (-1) 1 Fb^2/EJ = [3x - 3/2 x^2/b]_0^b Fb 1/EJ + 1 (-1) 1 Fb^2/EJ$$

$$= (3b - 3/2 b) Fb 1/EJ + 1 (-1) 1 Fb^2/EJ = 1/2 Fb^2/EJ$$

$$L_{DE}^{xo} = \int_0^b (3 - 6x/b + 3x^2/b^2) Fb 1/EJ dx = [3x - 3x^2/b + x^3/b^2]_0^b Fb 1/EJ$$

$$= (3b - 3b + b) Fb 1/EJ = Fb^2/EJ$$

$$L_{ED}^{xo} = \int_0^b (3x^2/b^2) Fb 1/EJ dx = [x^3/b^2]_0^b Fb 1/EJ$$

$$= (b) Fb 1/EJ = Fb^2/EJ$$

